

Operator's Manual RB-85W Broadcast Spreader

INTRODUCTION

Specifications, descriptions, and illustrative material in this literature are as accurate as possible. Specifications are subject to change without notice. Illustrations might include optional equipment and accessories, and might not include all standard equipment. Your equipment might appear slightly different than pictured equipment.



Read and understand all provided literature. Literature contains specifications and information for safety, operation, maintenance, storage, and assembly specific to this product. Scan QR codes for more information.



For additional literature, including safety manuals where applicable, or questions regarding terms used in this manual, visit:

https://www.echo-usa.com/manuals

OR






https://www.shindaiwa-usa.com/manuals

SERVICING INFORMATION

Parts and Serial Number

Genuine ECHO parts and assemblies for your ECHO products are available only from an Authorized ECHO Dealer. When you do need to buy parts always have the model number and serial number of the unit with you. For future reference write them in the space provided below.



Model No.	Serial No.	

Service

Service of this product during the warranty period must be performed by an Authorized ECHO Service Dealer. For the name and address of the Authorized ECHO Service Dealer nearest you, ask your retailer or call: 1-800-432-ECHO (3246). Dealer information is also available on our Web Site www.echo-usa.com. When presenting your unit for Warranty service/repairs, proof of purchase is required.

ECHO Consumer Product Support

If you require assistance or have questions concerning the application, operation, or maintenance of this product, call the ECHO Consumer Product Support Department at 1-800-432-ECHO (3246) from 8:00 a.m. to 5:00 p.m. (Central Standard Time) Monday through Friday. Before calling, please know the model and serial number of your unit.

Product Registration

Register your ECHO equipment online at www.echo-usa.com or by filling out the product registration sheet included in this manual. Registering your product confirms warranty coverage and provides a direct link to ECHO if we find it necessary to contact you.

Additional Literature

In addition to finding information online, information is available from your Authorized ECHO Service Dealer, or by contacting ECHO Incorporated, 400 Oakwood Road, Lake Zurich, IL 60047, 1-800-432-ECHO (3246).



SAFETY RB-85W

SAFETY

Safety Information

WARNING

Carefully read these instructions before use. Improper use or failure to follow instructions can result in product failure or injuries. For safe use of this product you must read and follow all instructions before using.


WARNING

Cancer and Reproductive Harm www.P65Warnings.ca.gov

WARNING

- Do not allow anyone to operate the broadcast spreader without proper instructions.
- Do not permit children to operate the broadcast spreader.
- Wear all personal protective equipment recommended by chemical manufacturer.
- Read and follow the chemical label instructions and warnings for handling and applying the chemicals you plan to spread – application settings provided are only a guideline.

DESCRIPTION



- 1 Handles
- 2 Hopper
- 3 Wheels
- 4 Adjustable Deflectors
- 5 Gate Control Rod
- 6 Gate Control Lever
- 7 Gate Adjustment Limiter



CONTENTS RB-85W

CONTENTS

The product you purchased has been partially factory pre-assembled for your convenience. Due to packaging restrictions, some assembly may be necessary.


After opening the carton, check for damage. Immediately notify your retailer or Dealer of damaged or missing parts. Use the contents list to check for missing parts.

- 1 Hopper Assembly
- 2 Wheels
- 1 Upper Handle Assembly
- 1 Gate Control Rod
- 1 Control Rod Adapter
- 1 Grate
- 1 Hopper Cover
- 1 6 mm Nut
- 1 Cotter Pin
- 5 6 mm Flange Nuts
- 2 6 x 60 mm Bolts
- 1 6 x 50 mm Bolt
- 1 Metal Washer
- 1 Nylon Washer
- 1 Rear Deflector
- 1 Operator's Manual
- 1 Warranty Statement


ASSEMBLY

Install Wheels and Handle

1. Install left wheel and secure with washer (A) cotter pin (B).




 Install right wheel and secure with 6 x 50 mm bolt (C) and 6 mm flange nut (D).




ASSEMBLY RB-85W

 Install upper handle assembly (E) into lower handle bracket (F), and secure with two 6 x 60 mm bolts (G) and two 6 mm flange nuts (H).




Install Gate Control Rod

 Insert tab end of gate control rod (C) into slotted hole in gate control lever (B). Turn rod clockwise until it is parallel with handle assembly.




RB-85W ASSEMBLY

 Thread 6mm nut (C) onto end of gate control rod to a distance of 25.4 mm (1 in) from bottom of rod. Insert threaded end of rod into hole in control rod adapter (D). Then thread 6 mm flange nut (E) onto gate control rod. Assure nuts remain spaced as shown.




 Attach control rod adapter to gate linkage (F). Secure with 6 mm flange nut (G) and nylon washer (H). Tighten nut until snug, then loosen nut 1/4 turn to allow hinge movement.




ASSEMBLY RB-85W

 Push control rod adapter (D) downward until gate is fully closed.




 Position gate control lever fully forward, and tighten control rod nut and flange nut as shown.



RB-85W ASSEMBLY

Install Grate

 Align notches in grate (A) with tabs (B) in hopper. Install grate into hopper. Turn grate clockwise to lock into place.



Rear Deflector

1. Install rear deflector (A) as shown.

Check Tire Pressure

NOTICE

Tires should be inflated to 15 psi. Assure tire pressure does not exceed 30 psi.

OPERATION RB-85W

OPERATION


Application Instructions

A CAUTION


TIP HAZARD. Unit can tip on uneven ground. Always fill hopper on flat ground, and keep bystanders away. Otherwise personal injury can result.

2. Adjust deflectors (C) to desired angle for spreading range.


Note: With deflectors closed, product will spread 1.07 m (3.5 ft). With deflectors fully open, product will spread 1.88 - 2.44 m (6-8 ft), depending on rate of travel.




 Pull gate control lever backward to set gate to desired opening size. Use gate adjustment limiter (B) to restrict gate opening size.



 Push gate control lever (A) fully forward to close gate. Fill hopper with product. Fill hopper in an area that won't be damaged by spilled product.



- Start spreader in motion, and pull gate control lever back to begin the flow of product.
- Move gate control lever forward to close gate before turning or stopping.




MAINTENANCE

Cleaning Spreader

NOTICE

Avoid spraying gear case directly, and do not use a pressure washer on spreader.

 Wash spreader with a garden hose after each use.




Lubrication

NOTICE

Lubricate gear case and axle once per season.

 Gear case and Axle: Clear debris from grease fittings (A). Apply 1-2 pumps of lithium-based grease with appropriate grease gun. Clean excess grease from grease fittings.



SPECIFICATIONS

MODEL	RB-85W
Length	1,194 mm (47 in.)
Width	654 mm (25.75 in.)
Height	952 mm (37.50 in.)
Weight	17.50 kg (38.50 lb.)
Capacity	
Weight	38.50 kg (85 lb.)
Volume	43.9 L (1.55 ft ³)
Loading Height	641 mm (25.25 in.)
Wheels and Tires	
Tire Diameter	305 mm (12in.)
Tire Type	Tubeless Pneumatic
Recommended Pressure	103.4 kPa (15 psi)

PRODUCT REGISTRATION

Thank you for choosing ECHO Power Equipment

Please go to http://www.echo-usa.com/Warranty/Register-Your-ECHO to register your new product on-line. It's **FAST** and **EASY!** NOTE: your information will never be sold or misused by ECHO, Incorporated. Registering your purchase enables us to contact you in the unlikely event of a service update or product recall, and verifies your ownership for warranty consideration.

If you do not have access to the Internet, you can complete the form below and mail to:

ECHO Incorporated, Product Registration, PO Box 1139, Lake Zurich, IL 60047.

$/\!\!/\!\!/$ Product registration card : Tarjeta de registro : carte d'enregistrement du produit

CONON	www echo-itsa com
ortorio.	product illigiting and special oriers. Simply go to.
Dinnoid	product information and enocial offere. Simply go to:
producto	De aleited of product appares allowing be sell flew Collo
allolle	he sleeted of product undates and/or he sent new FOHO
chorno	ONLINE OF ION: Register of III early save a starring for will
OPCIO	ONI INE OBTION: Degister ealine and save a stamp Verrarill

lease Print : Por Favor Enscriba Con Letra De Molde : En Lettre Carré S.V.P.

Purchaser's Name : Nombre del Comprador : Nom de l'acheteur

Address : Dirección : Adresse

na estampillar Le alertarán sobre actualizaciones del y/o se le enviara información sobre los nuevos pro-ECHO y las ofertas especiales. Simplemente visite: Registrese en la pagina web I POR INTERNET:

OPTION EN LIGNE: Enregistrer en ligne et épargner un timbrel Vous serez informé sur les nouveaux produits ECHO et les mises à jour de produit ainsi que, les offres spéciales.

www.echo-usa.com	Simplement Visitez le: WWW.ecno-usa.com
-ettre Carré S.V.P.	Confidential: Information provided will not be shared or sold
eur	Primary use of tool: ☐ Professional ☐ Homeowner ☐ Rental Equip. Uso primario de la herramienta:☐ Profesional ☐ Dueño de casa ☐ Aquiller. Usage principal:☐ Professionnel ☐ Residential ☐ Location
	Do you wish to receive periodic ECHO product information and special offers by e-mail?
	¿Desaa usted recibir información periódica y ofertas especiales por correo electronico sobre el producto ECHO? □ Yes □ No
Zip Code : Código Postal : Code Postal	Souhaitez-vous recevoir périodiquement de l'information sur les produits ECHO et les offres spéciales par courrier électronique ? Oui
	Did you visit the ECHO website before purchasing your product? ☐ Yes ☐ No
· Électronique	Visitó usted la pagina web ECHO antes de comprar su producto? □ Sí □ No

Avez-vous visité le site d'ECHO avant de procurer votre produit?

What factor(s) most influenced your purchase?

₽ □

ino 🗖

Date of Purchase: Fecha de la Compra

Date de l'achat

Phone Number: Número De Teléfono: Téléphone

E-Mail Address : Dirección De Correo Electrónico : Courrier Electronique

State: Estado:

Province

□ Price

	Date de l'achat	☐ Performance
		☐ Reliability
		☐ Friend/Family
mbre del Almacén donde fue Comprado : Lieu d'achat	ıprado : Lieu d'achat	¿Qué factor(es)
		☐ Funcionamiento
		☐ Confiabilidad
		☐ Amino/Familia

Where Purchased: No

33	2	O	G	
le plus				
eurs) vous a influencé	□ Prix	☐ Expérience	x you in the unlikely event of a service update or product recall and verifies your ☐ Ami/Famille ☐ Marque ☐ G	
Quel facteur (fact	□ Performance	☐ Fiabilité	☐ Ami/Famille	
o. de série	_		verifies your	cualquier evento
rie: No	_		ecall and	le cualqu
de Se	_	-	oduct re	ed en caso de c
: Numero	_		It of a service update or product reca	con usted er
umber	_	-	service	contacto (
Serial No	_		, event of a	estar en c
le modéle			Registering your purchase enables us to contact you in the unlikely event of a service update or p	a nos permite
e on : or			act yon i	n compre
Modelc			s to cont	egistrar s
' Number : Numero del Modele			enables u	oss.: El re
: Nun			urchase	vent of i
Number			d your b	o in the e
Model I			Registeri	wnershi

X7572270206 02-2012 ECHO Incorporated 400 Oakwood Rd., Lake Zurich, IL 60047 ☐ Garantie 1800 432 ECHO WWW ECHO USA COM

Marchand

Qualité

☐ Distribuidor

tor(es) influenció más en su compra?

/Family amiento

☐ Precio Brand

☐ Prior Experience

Calidad Garantía

Experiencia Anterior

☐ Marca

☐ Warranty

☐ Dealer Ouality

Registerior up un purchase anables us to contact viou in the unitide event of a service update or protect result and verifies y commissiping from the united protection of the use of contact of the united protection of the united of the unit

City: Ciudad: Ville

NOTES RB-85W

NOTES



N31100001001 - N31100999999



400 Oakwood Road

Lake Zurich, IL 60047 www.echo-usa.com