

CONTROLLER

AC Powered Controller

The LR-IS is an AC-powered Bluetooth® and LoRa[™] irrigation controller capable to program 24VAC solenoid valves sequentially. It is ideal for indoor installations. Paired with a Wi-Fi or 4G gateway, it can be remotely controlled from anywhere.

Compatibility	24VAC
Range to gateway	800* m / 875* yds
Stations	2/4/6/9/12
Power	24 VAC
Inputs	or or \mathbb{Q}^{*}
Connection	
Control	À distance

6 SOLEM

. 0

*Up to 800m range, variable depending on installation configuration.

INSTALLATION

External transformer 230V/24VAC Electrical connection terminal block Flowmeter or rain sensor connection Master valve Solenoid connection 24V Environment : from 0°C to 50°C Possible programming : start time, programs ... Yellow wire* : rain sensor connection or pulse contactor of a water meters

OPERATION

Power supply: 230 V-50 Hz / 24 V-50 Hz Conso. max.: 0,75 A (18VA) Surge protection at 4kV Bluetooth® Smart 4.2 Low Energy LoRa[™] radio communication Permanent backup of the programming Save the time in case of power failure at least 10 hours

DIMENSIONS Width: 11 - 16 cm Height: 14,5 cm Depth: 3,6 - 4,2 cm



*The yellow wire allows to act locally on the controllers but also on others through a setting on MySOLEM.





Accurate and easy to use

Autonomous once the programming has been sent. Location automatically saved thanks to the smartphone geolocation of the smartphone during installation in the valve box.



Radio LoRa[™]

Unmatched LoRaTM radio range (a minimum of 5 times better than radios standards) between the LR-MB or LR-BST gateway and your LR-IS-FL programmer.



MySOLEM

Remote control from MySOLEM App and platform.



Control your water consumption

Supervise continuously the flow of water consumed on each station and detect leakage or abnormal consumption instantly.



S MySOLEM

MAKE IT SIMPLE

Program your irrigation easily with MySOLEM app. Free & optimized for most devices.





Irrigation professionals can access up-to-date features on our free internet management platform at **MySOLEM.com**.