Operational Process for J SERIES LED Color Pool and Spa Lights

Important Note: All fixtures must be tied into the same transformer, circuit or switch for synchronization

POWERING ON THE J SERIES LED LIGHTS

1. Turn lights on. Lights will come on displaying the last color mode they were on prior to being turned off. (If this is the initial installation, the lights will return to whatever mode they were in when last receiving power).

If all Lights are in sync you may advance to Step **2** if you wish to change to another color or color show. If Lights are **not** in sync then skip Step **2** and proceed to Step **4**. Once Lights are in sync and on Position # 1, you can continue to Step **2** to select your desired color or color show.

OPERATING/ADVANCING THROUGH 9 FIXED COLORS & 5 COLOR SHOWS

- 2. To move to another color mode, cycle the Lights OFF/ON within 5 seconds. Each off/on cycle advances the program 1 step.
- 1. Alpine White
- 2. Sky Blue
- 3. Cobalt Blue
- 4. Caribbean Blue
- 5. Spring Green
- 6. Emerald Green
- 7. Emerald Rose
- 8. Magenta
- 9. Violet
- 10. Slow Color Splash
- 11. Fast Color Splash
- 12. America
- 13. Fat Tuesday
- 14. Disco Tech
- The Lights have memory. If the Lights are off over 10 seconds, the next time the Lights are turned on, they will turn on to the last color mode they were on prior to being turned off (Step 1 above). This function allows you to keep your Light returning to your favorite color mode every time the lights are turned back on.

4. LIGHT SYNCHRONIZATION

J Series Lights may be operated independently or together depending on the initial installation of your Lights. All J Series Lights that are wired to the same 12V Transformer/Switch will synchronize their operation of the above 14 Colors & Shows. If they do get out of synch, turn the switch ON then back OFF – wait 5 seconds and turn the switch back ON. They should now all be on Position #1 (Alpine White). You can now go back to Step **2** and cycle Power until you reach your desired Color or Color Show.

NOTE: At NO TIME shall the J Series lights be used in conjunction with any other lights including Savi standard LED nicheless lights. The color choices, shows and operations are <u>entirely different</u>

